

RZ1A1A30S-1

| | | |
|-----------------------|----------------|---------------------------|
| Switching Capacity | | 6000/saat |
| Connection Type | | 8 Pins |
| Operating Current | | 0.04A |
| Operational Frequency | | 50 Hz |
| Operational Voltage | | 12VAC/DC |
| Product | | Electronic Relay |
| Control | | Analog |
| Type | | Time |
| Contact | | 1CO |
| Current | Ie | 5A (rezistif) |
| Power Consumption | | 0.6W |
| Mechanical Life | Min Qty | 10000000 |
| Electrical Life | Min Qty | 100000 |
| Operating Temperature | | -5°C...+55°C |
| Protection Degree | | IP30 |
| Contact Material | | AgNi |
| Time Interval | | 0,03sec-30sec |
| Maximum Contact Power | | 150 W, 1,250 VA |
| Number of Contact | | 1 changeover |
| Repeat Accuracy | | ±%3 |
| Max. Reset Time | | ≤100ms |
| Voltage Interval | | (0,85-1.1)*Ue |
| Indicator | | Led |
| Serial | | RZ1 Series |
| Specifications | | Compact design |
| | | Fast and silent switching |
| | | Long life |
| | | Fingerproof design |